

Leica Wild TA 410 edge plotters with suction beam + control calculator + accessories



Leica Wild TA 410 edge plotters with suction beam + control calculator + accessories

Technical data:

operating range with tangential head in 1200 x 1270 mm
operating range with binary plotter head in 1140 x 1218 mm

Dimensions (L x B x H) in 1800 x in 1960 x 880
Weight 370 kg
Maximum speed 1000 mm / s.
Acceleration 10 m / s²
Resolution 0.01 mm
addressable resolution 0.01 mm
Static repetition ± 0.02 mm

Software-data format HPGL / emulations
Hardware interface RS232C (100..19200 Baud)
Input buffer 190 KB

Electricity supply 230 VAC $\pm 10\%$
optionally: 100,115,130,200,210 VAC $\pm 10\%$
50/60 hertz
Achievement 1300 VA

Accessories:

- Knife set
- Spare guts heads
- different feather heads
- Ballpoint- pencil
- Consumption materials (lubricating oils and greases)



Please only contact us via our registration form and only if you are a business person yourself. Every offer is subject to prior sale and includes your acceptance to our terms & conditions [Terms and conditions \(AGB\)](#). All logos and trademarks on this site are the property of their respective owners.

You will always receive an invoice including tax, which can be paid via wire transfer, in advance or cash. If you register on paypal, you may also pay by charging your paypal account with your credit card. If you are an EU member and you have a validated tax number which can be validated here: [VIES VAT number validation / MwSt.-Informationsaustauschsystem MIAS\) Validierung der MWSt.-Nummer](#) then you pay tax-free. If you are from outside the EU, you can only pay tax-free, if the export is done with the transport company, called 'Schenker'. If you are not using 'Schenker', we cannot guarantee that we will get the export confirmation in time. In that case, you have to pay tax and you get it.



**Brakensiek Systemhaus
GmbH & Co. KG**
Klönnestraße 94
D-44143 Dortmund

www.brakensiek.com

 **+49(0)231.985-00 10**

 **+49(0)231.985-2000**

BRAKENSIEK®
SYSTEMHAUS

Tim Brakensiek